

LG VX5500—BLUETOOTH® CAMERA PHONE

CAMERA

- VGA Camera
- Self Timer: Off, 3, 5, or 10 Seconds
- Color Effects: Normal, Negative, Aqua, Sepia, Black & White
- White Balance: Auto, Sunny, Cloudy, Fluorescent, Glow
- Dedicated Camera Key
- Camera Resolution: 640 x 480 (default), 320 x 240, 160 x 120 Pixels
- Image Editor – Zoom, Rotate, Crop

BLUETOOTH

- Bluetooth Profiles Supported: Headset, Hands-free, Object Push for vCard and vCalendar, Phone Book Access

SERVICES

- Text, Picture, & Voice Messaging
- Mobile Web mail, Mobile IM, & Chat
- Media Center Capable – Download Games, Ringtones, & More
- Mobile Web 2.0
- Device Software Update: Download Software Upgrades Over the Air
- VZ NavigatorSM Capable
- Chaperone Parent/Child capable
- Voicemail
- Handset Insurance - Yes

GENERAL

- Tools: Calculator, EZ Tip Calculator, Calendar, Alarm Clock, Stopwatch, World Clock, Notepad
- Speakerphone with dedicated speakerphone key
- Voice Commands
- Embedded Ringtones, Vibrating Alerts & Silent
- Phonebook with up to 1000 Entries with Multiple Contacts
- TTY Capable
- Bilingual Interface: English and Español
- In Case of Emergency Contacts

SPECIFICATIONS

- Frequency: 1.9 GHz CDMA PCS, 800 MHz CDMA
- Data Transmission: 1xRTT Voice & Data Capable
- Dimensions: 3.56" (H) x 1.84" (W) x 0.73" (D)
- Weight: 3.05 oz.
- Hearing Aid Compatibility = M4/T4
- SAR: Head .953 W/kg, Body .643 W/kg
- Internal LCD: 262K Color TFT, 176 x 220 Pixels, 1.76"
- External LCD: 65K Color TFT, 96 x 64 Pixels, 1.04"
- Usage Time: Up to 300 Minutes OR
- Standby Time: Up to 440 Hours

The Wireless Devices Group introduces the LG VX5500 to the Indirect product line-up! This launch is dependent upon the sell thru of the LG VX5400.



•VGA Camera

•Bluetooth Headset Support

•VZ Navigator Capable

•Mobile Web 2.0



Looking for a phone with streamlined good looks and user-friendly features? The LG VX5500 combines essential functionality and mobile fun. Snap pix of life's greatest moments and share them instantly. Use voice-activated dialing to call, then talk hands-free with the one-touch speakerphone or go completely wireless using the Bluetooth capability. All this wrapped into a stylish compact design with a large, easy-to-use keypad. Take advantage of the VX5500 where mobility has been so convenient.

SKU/UPC	Mock-Up	Vision
LG-VX5500 652810814140	LG-VX5500DP	13703

Each VX5500 is packaged with:

- Standard Li-Polymer Battery (950 mAh)
- Wall Charger
- User Guide
- Quick Reference Guide
- Battery Door

LG VX5500 Accessories

Micro USB Vehicle Power Charger
MICUSBVPC



Standard Li-Ion Polymer Battery (950mAh) In Box
LGINTBATS



Same as the LG VX8350/5400

Extended Li-Ion Polymer Battery (1500mAh) includes battery cover
LGINTBATX



Same as the LG VX8350/5400
Limited Stock

Micro USB Wall Charger
MICUSBTVL



Standard Battery Cover
LG5500BATDR



Extended Battery Cover
LG5500BATXDR



Direct Fulfillment

Fitted Leather Case w/Swivel Clip
LG5500CAS



Swivel Holster
LG5500HOL



Body Glove Sport Pouch
BGPCHM1



Launch packet accessories support the initial launch of this device. Accessories and part #'s may change throughout the course of the handset life. Always refer to the accessory section of the Equipment Guide to view most updated accessories listing. Click on accessory link found on the Equipment Guide

LG VX5500— BLUETOOTH® MONO

**Motorola H695
Bluetooth Headset**
MBT695Z



Talk time: Up to 8 hours
Standby time: Up to 200
hours

**Jawbone w/Noise
Shield Technology**
JAW2BTHS



Talk time: Up to 6 hours
Standby time: Up to 350
hours

**Plantronics 520
Bluetooth Headset**
PBT520Z



Talk Time: Up to 8 hours
Standby Time: Up to 180
hours

**Samsung WEP707
Bluetooth Headset**
SBT707Z



Talk Time: Up to 6 hours
Standby Time: Up to 200
hours

VZ Navigator



VZ NavigatorSM comes pre-loaded on your New Samsung SCH-u430! This application allows customers to map their location, find nearby points of interest and get audible turn-by-turn directions right on their wireless handset! VZ NavigatorSM is the first consumer product from Verizon Wireless using the benefit of Location Based Services technology. VZ NavigatorSM combines geographic location information with turn-by-turn navigation, and points-of-interest lookup accessible right from a wireless handset.

Feature

Advantage

Benefit

Audible Turn-by-Turn Directions	Provides users with audible directions to help them navigate to a destination or location	<u>Safety & Convenience</u> – “With audible turn-by-turn directions, VZ NavigatorSM makes your navigation efficient and safe without maps or paper directions!”
Location Mapping	Displays a user’s position on a map via the GPS satellite network	<u>Confidence</u> – “Never feel lost again! With VZ NavigatorSM your handset becomes your audio road atlas to find your destination!”
Point of Interest Lookup	Helps customers find nearby restaurants, banks, stores, ATMs based on their current GPS location	<u>Awareness</u> – “Always know what’s nearby and how to get where you want to go! VZ NavigatorSM puts you in the know!”

VZ NavigatorSM Requires Location On

To Set Location On:

1. From the main screen, press the Center Select Key
2. Press (9) “Settings & Tools.”
3. Press (6) “Phone Settings”
4. Press (5) “Location.”
5. “Location On” is highlighted. Press the Center Select Key for OK.


To Access VZ NavigatorSM :

1. From the main screen, press the Center Select Key
2. Press (8) “VZ Navigator”

Bluetooth Pairing

How to Pair Your Device

1. Press OK to enter the Menu.
2. Press the Directional key UP to highlight Settings & Tools and press OK.
3. Press 3 for Bluetooth Menu
4. Press 1 for Add New Device
5. If Bluetooth is set to OFF, the phone will prompt you to turn Bluetooth on, Press OK for Yes.
6. Follow the directions in your Bluetooth Accessory's user guide to set the device into pairing mode and press OK.
7. Once found, the device will appear on the display.
8. Highlight the device to be paired and press OK for PAIR.
9. The phone may automatically try to pair. If auto-pairing fails, enter the passkey (typically 0000).
10. Once paired press OK to connect.



Helpful Hints

Manually Programming the VX5500

1. With the flip open, use the keypad to enter **#++ + P+R+O+G+R+A+M+5+5+0+0+Send Key**.
2. Enter **0 0 0 0 0 0** as the service code.
3. Press **OK** for **Service Prg. (1)**.
4. Press **OK** to continue.
5. Input the **Phone number (MDN)** and press **OK**.
6. Input the **Phone number (MIN)** and press **OK**.
7. Input the **NAM1 Home SID** and press **OK**.
8. Input the **NAM1 Name** and press **OK**.
9. When programming is successful, the phone will confirm, "**NAM1 Completed.**"
10. Press the **Left Soft Key** for **Exit**. The phone will then power down.

OTA Instructions

1. Perform the usual billing system activation procedure.
2. With the flip open, use the keypad to enter ***+2+2+8+Send Key**.
3. The following audio message will be heard:
"Welcome to Verizon Wireless over-the-air programming. This call is airtime free. To program your phone, press '1'. To update your roaming capabilities, press '2'."
Note: Programming will take up to 2 minutes. Should the programming exceed 45 seconds, the following audio message will be repeated at 25-second intervals: "Please continue to hold while your phone is being programmed."
4. You will hear an audio message once the phone has been successfully programmed.

How to View the Software, PRL, ERI, and Browser Version:

1. With the flip open, press the **OK Key** to enter the main menu.
2. Select **Settings & Tools (9)**.
3. Select **Phone Info (9)**.
4. Select **SW/HW Version (2)**.

IP Address Programming

1. With the flip open, use the keypad to enter **#++ + P+R+O+G+R+A+M+5+5+0+0+Send Key**.
2. Enter **0 0 0 0 0 0** as the service code.
3. Select **WAP Setting (5)**. You may then choose from:
 1. Proxy Address Setting
 2. Proxy Port Setting
 3. TLS/HTTPS Security Port Setting
 4. User Name
 5. User Password
 6. Homepage

How to Send a Text Message

1. With the flip open, press the **Left Soft Key** for **Message**.
2. Press **OK** for **New Message (1)**, and then choose **TXT Message (1)**.
3. Enter the recipient's phone number, or press the **Right Soft Key** to choose someone from your contacts or recent calls list.
4. Press **OK** and enter your **message** (up to 160 characters) using the alphanumeric keypad. You may select an alternate text entry mode by pressing the **Left Soft Key**.
5. Press the **OK Key** when you are finished to send the message.

How to Access the Web

1. With the flip open, press **up** on the **Directional Key** to access the mobile web.
2. Choose a **category**, or press the **Right Soft Key** and select **Go To URL (4)**.

Click on the link below to view technical information for the database management group.

[VX5500](#)

Features – Advantage - Operation

Feature	Advantage	Operation
Bluetooth Capable for certain profiles	Multiple supported profiles with the ability to save up to 20 different pairings.	<ol style="list-style-type: none"> 1. Set your Bluetooth accessory into pairing mode.* 2. From standby mode and with the flip open, press the OK Key and then select Settings & Tools (9). 3. Select Bluetooth Menu (3) and then Add New Device (1). 4. If Bluetooth is off, you will be prompted to turn it on by pressing the OK Key. 5. Press the OK Key to begin searching for the accessory. Once it is found, highlight it and press the OK Key to pair.* 6. Press the OK Key to connect with the device. <p>*Refer to your Bluetooth accessory's user guide for information about initiating pairing mode and the passkey if asked (typically "0000"). If the accessory supports the headset/hands-free profile, your phone will automatically pair for you without having to input the passkey.</p>
VGA Camera	Zoom, rotate, crop, resize, and add fun frames to your images with the VX5500's image editor. Self-portrait capabilities with the flip closed.	<ol style="list-style-type: none"> 1. From standby mode and with the flip open, press the side Camera Key. 2. Press left or right on the Directional Key to zoom.* Press up or down to adjust the brightness. Press the Right Soft Key to access additional camera options. 3. Press the OK Key to take a photo. 4. Press the Left Soft Key to save the picture, or press the OK Key to send it. <p>Note: To take a self-portrait with the flip closed, press and <i>hold</i> the side Camera Key, and then quickly press the side Volume Keys. Press the side Camera Key again to take a picture.</p> <p>*Camera setting of 640 x 480 pixels does not support zoom function.</p>
Object Push for vCard and vCalendar Events via Bluetooth	Send all contacts and calendar events via Bluetooth.	<ol style="list-style-type: none"> 1. From standby mode and with the flip open, press the Right Soft Key for Contacts. 2. Select a contact from the list, and then press the Right Soft Key for Options. 3. Select Send Name Card (9) and then Via Bluetooth (4). You can select all contacts by pressing the Right Soft Key for Options and then choosing Mark All (2). 4. When you're finished, press the Left Soft Key for Done. 5. You will be prompted to select a device to send the contact(s) to. With the device highlighted, press the OK Key.